



ASHRAE STANDARD

Method of Test for Conformance to BACnet[®]

Approved by the ASHRAE Standards Committee on June 20, 2009; by the ASHRAE Board of Directors on June 24, 2009; and by the American National Standards Institute on June 25, 2009.

This standard is under continuous maintenance by a Standing Standard Project Committee (SSPC) for which the Standards Committee has established a documented program for regular publication of addenda or revisions, including procedures for timely, documented, consensus action on requests for change to any part of the standard. The change submittal form, instructions, and deadlines may be obtained in electronic form from the ASHRAE Web site, <http://www.ashrae.org>, or in paper form from the Manager of Standards. The latest edition of an ASHRAE Standard may be purchased from ASHRAE Customer Service, 1791 Tullie Circle, NE, Atlanta, GA 30329-2305. E-mail: orders@ashrae.org. Fax: 404-321-5478. Telephone: 404-636-8400 (worldwide), or toll free 1-800-527-4723 (for orders in US and Canada).

© Copyright 2009 American Society of Heating, Refrigerating and Air-Conditioning Engineers, Inc.

ISSN 1041-2336



**American Society of Heating, Refrigerating
and Air-Conditioning Engineers, Inc.**
1791 Tullie Circle NE, Atlanta, GA 30329
www.ashrae.org

ASHRAE Standing Standard Project Committee 135
Cognizant TC: TC 1.4, Control Theory and Application
SPLS Liaison: Frank E. Jakob

William O. Swan, III, <i>Chair*</i>	A. J. Capowski	J. Damian Ljungquist*
David Robin, <i>Vice-Chair</i>	Troy Cowan	James G. Luth*
Carl Neilson, <i>Secretary</i>	Sharon E. Dinges*	John J. Lynch
Donald P. Alexander*	Thomas Ertsgaard	Mark A. Railsback
David J. Branson	Craig P. Gemmill	Carl J. Ruther*
Barry B. Bridges*	Daniel P. Giorgis	David G. Shike*
Coleman L. Brumley, Jr.*	David G. Holmberg*	David B. Thompson*
Ernest C. Bryant*	Robert L. Johnson*	Daniel A. Traill
James F. Butler	Stephen Karg	J. Michael Whitcomb
Steven T. Bushby		David F. White

**Denotes members of voting status when the document was approved for publication*

ASHRAE STANDARDS COMMITTEE 2008–2009

Hugh F. Crowther, <i>Chair</i>	Jay A. Kohler
Steven T. Bushby, <i>Vice-Chair</i>	Carol E. Marriott
Robert G. Baker	Merle F. McBride
Michael F. Beda	Frank Myers
Donald L. Brandt	H. Michael Newman
Paul W. Cabot	Janice C. Peterson
Kenneth W. Cooper	Douglas T. Reindl
Samuel D. Cummings, Jr	Lawrence J. Schoen
K. William Dean	Boggarm S. Setty
Martin Dierycxk	Bodh R. Subherwal
Robert G. Doerr	William F. Walter
Allan B. Fraser	Michael W. Woodford
Nadar R. Jayaraman	David E. Knebel, <i>BOD ExO</i>
Byron W. Jones	Andrew K. Persily, <i>CO</i>

Stephanie Reiniche, *Manager of Standards*

SPECIAL NOTE

This American National Standard (ANS) is a national voluntary consensus standard developed under the auspices of the American Society of Heating, Refrigerating and Air-Conditioning Engineers (ASHRAE). *Consensus* is defined by the American National Standards Institute (ANSI), of which ASHRAE is a member and which has approved this standard as an ANS, as "substantial agreement reached by directly and materially affected interest categories. This signifies the concurrence of more than a simple majority, but not necessarily unanimity. Consensus requires that all views and objections be considered, and that an effort be made toward their resolution." Compliance with this standard is voluntary until and unless a legal jurisdiction makes compliance mandatory through legislation.

ASHRAE obtains consensus through participation of its national and international members, associated societies, and public review.

ASHRAE Standards are prepared by a Project Committee appointed specifically for the purpose of writing the Standard. The Project Committee Chair and Vice-Chair must be members of ASHRAE; while other committee members may or may not be ASHRAE members, all must be technically qualified in the subject area of the Standard. Every effort is made to balance the concerned interests on all Project Committees.

The Manager of Standards of ASHRAE should be contacted for:

- interpretation of the contents of this Standard,
- participation in the next review of the Standard,
- offering constructive criticism for improving the Standard, or
- permission to reprint portions of the Standard.

DISCLAIMER

ASHRAE uses its best efforts to promulgate Standards and Guidelines for the benefit of the public in light of available information and accepted industry practices. However, ASHRAE does not guarantee, certify, or assure the safety or performance of any products, components, or systems tested, installed, or operated in accordance with ASHRAE's Standards or Guidelines or that any tests conducted under its Standards or Guidelines will be nonhazardous or free from risk.

ASHRAE INDUSTRIAL ADVERTISING POLICY ON STANDARDS

ASHRAE Standards and Guidelines are established to assist industry and the public by offering a uniform method of testing for rating purposes, by suggesting safe practices in designing and installing equipment, by providing proper definitions of this equipment, and by providing other information that may serve to guide the industry. The creation of ASHRAE Standards and Guidelines is determined by the need for them, and conformance to them is completely voluntary.

In referring to this Standard or Guideline and in marking of equipment and in advertising, no claim shall be made, either stated or implied, that the product has been approved by ASHRAE.

[This foreword and the “rationales” on the following pages are not part of this standard. They are merely informative and do not contain requirements necessary for conformance to the standard.]

FOREWORD

This addendum describes changes to the current standard. These modifications are the result of change proposals made pursuant to the ASHRAE continuous maintenance procedures and of deliberations within Standing Standard Project Committee 135. The changes are summarized below.

- 135.1-2007b-1. Omit certain tests when Averaging and Command properties are fixed or not present, p. 1.
- 135.1-2007b-2. Accommodate Group objects whose members list is not changeable, p. 3.
- 135.1-2007b-3. Revise Alarm Acknowledgement tests, p. 5.
- 135.1-2007b-4. Add new Alarm Acknowledgement "offnormal" tests, p. 8.
- 135.1-2007b-5. Label conditionally-writable properties in the EPICS, p. 10.
- 135.1-2007b-6. Add new object types, p. 11.

In the following document, language to be added to existing clauses of ANSI/ASHRAE 135.1-2007 is indicated through the use of *italics*, while deletions are indicated by ~~strike through~~. Where entirely new subclauses are to be added, plain type is used throughout.

135.1-2007b-1. Omit certain tests when Averaging and Command properties are fixed or not present.

Rationale

Several tests for the Averaging and Command objects make no provision for being skipped if relevant optional properties are not present or if the object has a fixed configuration.

Addendum 135.1-2007b-1

[Change 7.3.2.4.2, p. 56.]

7.3.2.4.2 Managing the Sample Window

Purpose: To verify that an Averaging object correctly tracks the average, minimum, and maximum values attained in a sample. This includes monitoring before and after the sampling window is full.

Test Concept: An Averaging object is configured to monitor a property that can be controlled manually by the testing agent or by the TD. The TD initializes the sample and then monitors the Minimum_Value, Average_Value, Maximum_Value, Attempted_Samples, and Valid_Samples properties after each sampling interval to verify that their values are properly tracking the monitored value. This requires the ability to manipulate the values of the monitored property value and a slow enough sampling interval to permit the analysis. This continues until after the sample window is full. *If the IUT does not support Averaging object configuration, then this test shall be omitted.*

Configuration Requirements: The IUT shall be configured with an Averaging object used to monitor a property that can be controlled by the testing agent or by the TD. The sampling interval shall be configured to allow time to change the monitored property value and to determine if each of the properties Minimum_Value, Average_Value, Maximum_Value, Attempted_Samples, and Valid_Samples correctly changes after each sample interval.

[Change 7.3.2.9.1, pp. 61.]

7.3.2.9.1 All Writes Successful with Post_Delay Test

Dependencies: ReadProperty Service Execution Tests, 9.18; WriteProperty Service Execution Tests, 9.22.

BACnet Reference Clause: 12.9.8.

Purpose: To verify that a Command object can successfully execute an action list that includes post delays.

Test Concept: The IUT is configured with an action list that includes manipulating a sequence of externally visible outputs with a time delay between each output. The TD triggers this action list and the tester observes the external changes. *If the IUT does not support Post Delay, then this test shall be omitted. If the IUT does not support action list configuration for this Test Concept, then this test shall be omitted.*

Configuration Requirements: The IUT shall be configured with a Command object having an action list, X, that includes writing to a sequence of externally visible outputs. There shall be a post delay between writes to the externally visible outputs that is long enough for the tester to observe the delay.

[Change 7.3.2.9.2, p. 62.]

7.3.2.9.2 Quit on Failure Test

Dependencies: ReadProperty Service Execution Tests, 9.18; WriteProperty Service Execution Tests, 9.22.

BACnet Reference Clause: 12.9.8.

Purpose: To verify that a Command object can successfully execute Quit_On_Failure procedures.

Test Concept: The IUT is configured with two action lists that include a sequence of externally visible outputs with a write somewhere in the sequence that will fail. The action lists are identical except that one has `Quit_On_Failure` set to `TRUE` and the other set to `FALSE`. The TD triggers both action lists. The external outputs are observed to verify that the failure procedures are properly implemented. *If the IUT does not support action list configuration for this Test Concept, then this test shall be omitted.*

Configuration Requirements: The IUT shall be configured with a Command object having at least two action lists, X and Y, that includes writing to a sequence of externally visible outputs. Somewhere in the sequence there shall be a write command that will fail that is followed by write commands that will succeed. Both action lists shall be identical except that list X shall have `Quit_On_Failure` set to `TRUE` and Y shall have `Quit_On_Failure` set to `FALSE`.

[Change 7.3.2.9.4, p. 63.]

7.3.9.2.4 Empty Action List Test

Dependencies: WriteProperty Service Execution Tests, 9.22.

BACnet Reference Clause: 12.9.8.

Purpose: To verify that a Command object takes no action when `Present_Value` is written to with a non-zero value that corresponds to an empty action list.

Test Concept: The IUT is configured with at least one empty action list. The TD triggers the action list. The external outputs are observed to verify that no changes occurred. If the IUT does not support action list configuration for this Test Concept, then this test shall be omitted.

Configuration Requirements: The IUT shall be configured with a Command object that has an Action property with at least one empty action list.

[Change 7.3.2.9.7, p. 64.]

7.3.9.2.7 Write While In_Process is TRUE Test

Dependencies: WriteProperty Service Execution Tests, 9.22.

BACnet Reference Clauses: 12.9.8 and 12.9.9.

Purpose: To verify that an action list continues to completion if a second action list is commanded while `In_Process` is `TRUE` and that the second action list is not executed.

Test Concept: The IUT is configured with two action lists that include a sequence of externally visible outputs with post delays for each action. The TD triggers the first action list. The external outputs are observed in order to trigger the second action list during the post delay of the first list. The TD triggers the second action list. The external outputs are observed to verify that the second action list is not executed. If the IUT does not support Post Delay, then this test shall be omitted. If the IUT does not support action list configuration for this Test Concept, then this test shall be omitted.

Configuration Requirements: The IUT shall be configured with a Command object having two distinct action lists, X and Y, that include writing to a sequence of externally visible outputs. There shall be a post delay between writes to the externally visible outputs that is long enough for the tester to observe the delay (This ensures `In_Process` remains `TRUE` long enough to command the second action list).

135.1-2007b-2. Accommodate Group objects whose members list is not changeable.

Rationale

The Group Object (functionality) test should accommodate Group objects whose List_Of_Group_Members references one or more properties that are changeable.

Addendum 135.1-2007b-2

[Change 7.3.2.14, pp. 69-70.]

7.3.2.14 Group Object Test

Dependencies: ReadProperty Service Execution Tests, 9.18; WriteProperty Service Execution Tests, 9.22.

BACnet Reference Clause: 12.14.

Purpose: To verify that the Present_Value of a Group properly tracks the values of the properties of the objects that make up the group.

Test Concept: The Present_Value of a Group object is read. Each of the object, property combinations that make up the membership of the Group is also read. The values are compared to verify that they match. The value of one of the Group members is changed. The Present_Value of the Group is read again to verify that it correctly tracks the change.

Configuration Requirements: The IUT shall be configured with a Group object that has at least two members. One of the group members shall be changeable by the WriteProperty service or some other mechanism provided by the vendor. The value of the properties that make up the Group shall remain static for the duration of the test except for changes made as part of the test procedure.

Test Steps:

1. TRANSMIT ReadProperty-Request,
 'Object Identifier' = (the Group object being tested),
 'Property Identifier' = List_Of_Group_Members
2. RECEIVE ReadProperty-ACK,
 'Object Identifier' = (the Group object being tested),
 'Property Identifier' = List_Of_Group_Members,
 'Property Value' = (any valid list of group members)
3. TRANSMIT ReadProperty-Request,
 'Object Identifier' = (the Group object being tested),
 'Property Identifier' = Present_Value
4. RECEIVE ReadProperty-ACK,
 'Object Identifier' = (the Group object being tested),
 'Property Identifier' = Present_Value,
 'Property Value' = (any valid set of values consistent with the properties that make up the group)
5. REPEAT X = (each object, property combination returned in the List_Of_Group_Members in step 2) DO {
 VERIFY X = (the same value that was returned for this group member in step 4)}
6. IF (a property value of a group member is changeable) THEN
 IF (the changeable group member property value is writable) THEN
 WRITE (the writable property that is a member of the group) = (a value different from its current value)
 ELSE
 MAKE (the changeable group member property value different from its current value)
7. WAIT **Internal Processing Fail Time**
8. TRANSMIT ReadProperty-Request,
 'Object Identifier' = (the Group object being tested),
 'Property Identifier' = Present_Value
9. RECEIVE ReadProperty-ACK,

- 'Object Identifier' = (the Group object being tested),
'Property Identifier' = Present_Value,
'Property Value' = (the same set of values received in step 4 except for the value changed in step 6)
10. REPEAT X = (each object, property combination returned in the List_Of_Group_Members in step 2) DO {
 VERIFY X = (the same value that was returned for this group member in step 9)}

135.1-2007b-3. Revise Alarm Acknowledgement tests.

Rationale

Several revisions to Alarm Acknowledgement tests are made to improve the handling of different test situations and new error codes.

Addendum 135.1-2007b-3

[Change 9.1.2.3, p. 200.]

9.1.2.3 Unsuccessful Alarm Acknowledgment of Confirmed Event Notifications Because the 'Event Object Identifier' is Invalid Referenced Object Does Not Exist

Purpose: This test case verifies that an alarm remains unacknowledged if the 'Event Object Identifier' represents an object that does not exist or is not consistent with the other parameters that define the alarm being acknowledged.

Test Concept: An alarm is triggered that causes the IUT to notify the TD and at least one other device. The TD acknowledges the alarm using an improper 'Event Object Identifier' and verifies that the acknowledgment is not accepted by the IUT and that the IUT does not notify other devices that the alarm was acknowledged. The TD then acknowledges the alarm using the proper 'Event Object Identifier' and verifies that the acknowledgment is properly noted by the IUT. The IUT notifies all other recipients that the alarm was acknowledged.

Configuration Requirements: The IUT shall be configured with at least one object that can detect alarm conditions and send confirmed notifications. The Acked_Transitions property shall have the value B'111" indicating that all transitions have been acknowledged. The TD and at least one other BACnet device shall be recipients of the alarm notification.

Test Steps: The test steps defined in 9.1.2.1 shall be followed except that in the first AcknowledgeAlarm request the 'Time Stamp' shall have the same value as the 'Time Stamp' from the event notification, and the 'Event Object Identifier' shall have a value that is different from the 'Event Object Identifier' in the event notification *and for which no object exists in the IUT.*

Passing Result: A passing result is the same message sequence described in 9.1.2.1 except that the *Error Class in step 7 shall be OBJECT and the Error Code in step 7 shall be INCONSISTENT_PARAMETERS. UNKNOWN_OBJECT. For devices that claim a Protocol_Revision of 5 or prior, an Error Class of SERVICES with an Error Code of INCONSISTENT_PARAMETERS shall also be accepted.*

[Change 9.1.2.4, p. 200.]

9.1.2.4 Unsuccessful Alarm Acknowledgment of Confirmed Event Notifications Because the 'Event State Acknowledged' is Invalid

Purpose: This test case verifies that an alarm remains unacknowledged if the 'Event State Acknowledged' is inconsistent with the other parameters that define the alarm being acknowledged.

Test Concept: An alarm is triggered that causes the IUT to notify the TD and at least one other device. The TD acknowledges the alarm using an invalid event state and verifies that the acknowledgment is not accepted by the IUT and that the IUT does not notify other devices that the alarm was acknowledged. The TD then acknowledges the alarm using the proper event state and verifies that the acknowledgment is properly noted by the IUT. The IUT notifies all other recipients that the alarm was acknowledged.

Configuration Requirements: The IUT shall be configured with at least one object that can detect alarm conditions and send confirmed notifications. The Acked_Transitions property shall have the value B'111" indicating that all transitions have been acknowledged. The TD and at least one other BACnet device shall be recipients of the alarm notification.

Test Steps: The test steps defined in 9.1.2.1 shall be followed except that in the first AcknowledgeAlarm request the 'Time Stamp' shall have the same value as the 'Time Stamp' from the event notification and the 'Event State

Acknowledged' shall have an *off-normal* value *other than OFFNORMAL* and *other than the value of that is different from the 'To State' parameter* in the event notification.

Passing Result: A passing result is the same message sequence described in 9.1.2.1 except that the Error Code in step 7 shall be ~~INCONSISTENT_PARAMETERS~~. *INVALID_EVENT_STATE*. For devices that claim a *Protocol_Revision* of 5 or prior, an Error Code of *INCONSISTENT_PARAMETERS* shall also be accepted.

[Change 9.1.2.6, p. 203.]

9.1.2.6 Unsuccessful Alarm Acknowledgment of Unconfirmed Event Notifications Because the 'Event Object Identifier' is Invalid Referenced Object Does Not Exist

Purpose: This test case verifies that an alarm remains unacknowledged if the 'Event Object Identifier' represents an object that does not exist ~~or is not consistent with the other parameters that define the alarm being acknowledged~~.

Test Concept: An alarm is triggered that causes the IUT to notify the TD and at least one other device. The TD acknowledges the alarm using an invalid event object identifier and verifies that the acknowledgment is not accepted by the IUT and that the IUT does not notify other devices that the alarm was acknowledged. The TD then acknowledges the alarm using the proper event object identifier and verifies that the acknowledgment is properly noted by the IUT. The IUT notifies all other recipients that the alarm was acknowledged.

Configuration Requirements: The IUT shall be configured with at least one object that can detect alarm conditions and send unconfirmed notifications. The *Acked_Transitions* property shall have the value B'111" indicating that all transitions have been acknowledged. The TD and at least one other BACnet device shall be recipients of the alarm notification.

Test Steps: The test steps defined in 9.1.2.5 shall be followed except that in the first AcknowledgeAlarm request the 'Time Stamp' shall have the same value as the 'Time Stamp' from the event notification, and the 'Event Object Identifier' shall have a value that is different from the 'Event Object Identifier' in the event notification *and for which no object exists in the IUT*.

Passing Result: A passing result is the same message sequence described as the passing result in 9.1.2.5 except that the *Error Class* in step 7 shall be *OBJECT* and the Error Code in step 7 shall be ~~INCONSISTENT_PARAMETERS~~. *UNKNOWN_OBJECT*. For devices that claim a *Protocol_Revision* of 5 or prior, an Error Class of *SERVICES* with an Error Code of *INCONSISTENT_PARAMETERS* shall also be accepted.

[Change 9.1.2.7, p. 203.]

9.1.2.7 Unsuccessful Alarm Acknowledgment of Unconfirmed Event Notifications Because the 'Event State Acknowledged' is Invalid

Purpose: This test case verifies that an alarm remains unacknowledged if the 'Event State Acknowledged' is inconsistent with the other parameters that define the alarm being acknowledged.

Test Concept: An alarm is triggered that causes the IUT to notify the TD and at least one other device. The TD acknowledges the alarm using an invalid 'Event State Acknowledged' and verifies that the acknowledgment is not accepted by the IUT and that the IUT does not notify other devices that the alarm was acknowledged. The TD then acknowledges the alarm using the proper 'Event State Acknowledged' and verifies that the acknowledgment is properly noted by the IUT. The IUT notifies all other recipients that the alarm was acknowledged.

Configuration Requirements: The IUT shall be configured with at least one object that can detect alarm conditions and send unconfirmed notifications. The *Acked_Transitions* property shall have the value B'111" indicating that all transitions have been acknowledged. The TD and at least one other BACnet device shall be recipients of the alarm notification.

Test Steps: The test steps defined in 9.1.2.1 shall be followed except that in the first AcknowledgeAlarm request the 'Time Stamp' shall have the same value as the 'Time Stamp' from the event notification and the 'Event State Acknowledged' shall have an *off-normal* value *other than OFFNORMAL and other than the value of that is different from the 'To State' parameter* in the event notification.

Passing Result: A passing result is the same message sequence described as the passing result in 9.1.2.5 except that the Error Code in step 7 shall be ~~INCONSISTENT_PARAMETERS~~ *INVALID_EVENT_STATE*. *For devices that claim a Protocol_Revision of 5 or prior, an Error Code of INCONSISTENT_PARAMETERS shall also be accepted.*

135.1-2007b-4. Add new Alarm Acknowledgement "offnormal" tests.

Rationale

Addendum 135-2004d-3 clarified the acknowledgement of "offnormal" states where there are multiple such states (e.g., high-limit and low-limit). Tests are added for acknowledgements in such situations.

Addendum 135.1-2007b-4

[Add new clause 9.1.1.7 p. 196.]

9.1.1.7 Successful Alarm Acknowledgment of any "Offnormal" Transitions Using an "Offnormal" 'To State'

Purpose: To verify the successful acknowledgment of an alarm that indicated an "offnormal" 'To State' other than offnormal.

Test Concept: An "offnormal" alarm is triggered in the IUT where the "offnormal" state is represented by an event-state other than offnormal (such as high-limit or low-limit). The TD acknowledges the alarm with an 'Event State Acknowledged' of offnormal and verifies that the acknowledgment is accepted by the IUT.

Configuration Requirements: The IUT shall be configured with at least one object that can detect alarm conditions and can enter "offnormal" states other than offnormal. The TD shall be a recipient of the alarm notification and the IUT shall be configured to send it unconfirmed. If the IUT cannot be configured to generate such a notification, then this test shall be skipped.

Test Steps:

1. MAKE (a change that triggers the detection of an alarm event in the IUT)
2. RECEIVE UnConfirmedEventNotification-Request,
 - 'Process Identifier' = (the process identifier configured for this event),
 - 'Initiating Device Identifier' = IUT,
 - 'Event Object Identifier' = (the object detecting the alarm),
 - 'Time Stamp' = (the current time or sequence number),
 - 'Notification Class' = (the notification class configured for this event),
 - 'Priority' = (the priority configured for this event),
 - 'Event Type' = (any valid event type),
 - 'Notify Type' = (any valid notify type),
 - 'AckRequired' = TRUE,
 - 'From State' = (any valid event-state),
 - 'To State' = (any "offnormal" event state other than offnormal itself),
 - 'Event Values' = (the values appropriate to the event type)
3. VERIFY (the 'Event Object Identifier' from the event notification), Acked_Transitions = {0,?,?}
4. TRANSMIT AcknowledgeAlarm-Request,
 - 'Acknowledging Process Identifier' = (the value of the 'Process Identifier' parameter in the event notification),
 - 'Event Object Identifier' = (the 'Event Object Identifier' from the event notification),
 - 'Event State Acknowledged' = offnormal,
 - 'Time Stamp' = (the timestamp conveyed in the notification),
 - 'Time of Acknowledgment' = (any valid timestamp)
5. RECEIVE BACnet-Simple-ACK-PDU
6. IF (Protocol_Revision is present and Protocol_Revision \geq 1) THEN
 - RECEIVE UnconfirmedEventNotification-Request,
 - 'Process Identifier' = (the process identifier configured for this event),
 - 'Initiating Device Identifier' = IUT,
 - 'Event Object Identifier' = (the object detecting the alarm),
 - 'Time Stamp' = (the current time or sequence number),

'Notification Class' = (the notification class configured for this event),
'Priority' = (the priority configured for this event),
'Event Type' = (the event type included in step 2),
'Notify Type' = ACK_NOTIFICATION,
'To State' = (offnormal or the 'To State' from step 2)

ELSE
RECEIVE UnconfirmedEventNotification-Request,
'Process Identifier' = (the process identifier configured for this event),
'Initiating Device Identifier' = IUT,
'Event Object Identifier' = (the object detecting the alarm),
'Time Stamp' = (the current time or sequence number),
'Notification Class' = (the notification class configured for this event),
'Priority' = (the priority configured for this event),
'Event Type' = (the event type included in step 2),
'Notify Type' = ACK_NOTIFICATION,

7. VERIFY (the 'Event Object Identifier' from the event notification), Acked_Transitions = {1,?,?}

135.1-2007b-5. Label conditionally-writable properties in the EPICS.

Rationale

To allow the differentiation between properties that are always writable and those that are only writable under specific conditions, a new keyword is added to the EPICS language.

Addendum 135.1-2007b-5

[Change 4.5.10, pp. 11-12.]

4.5.10 Test Database

...

Properties in the test database that are writable shall have a "W" following the property value, as shown in the example below:

```
{
  object-identifier: (analog-value, 6)
  object-name: "□"
  object-type: analog-value
  present-value: 23.4 W
  other properties...
}
```

Properties in the test database that are conditionally writable shall have a "C" following the property value, as shown in the example below. It is recommended that the governing mechanism be identified in a comment:

```
{
  object-identifier: (analog-input, 6)
  object-name: "□"
  object-type: analog-input
  present-value: 12.3 C -- Writable when Out_Of_Service is TRUE
  other properties...
}
```

The following sections show templates for each of the standard object types. To improve readability the carriage return/linefeed pairs are not explicitly shown in the examples.

...

135.1-2007b-6. Add new object types.

Rationale

Several object types have been added to ANSI/ASHRAE Standard 135 since the 2001 version. This revision adds object types that appear in the 2004 version, plus those published in Addenda 135-2004d, e and f. This adds references to those objects only, not the tests for those objects.

Addendum 135.1-2007b-6

[Change 4.5.4, p. 9.]

4.5.4 Object Types Supported

...

The standard objects may be any of:

<i>Access Door</i>	Command	Multi-state Output
<i>Accumulator</i>	Device	Multi-state Value
Analog Input	Event Enrollment	Notification Class
Analog Output	File	Program
Analog Value	Group	<i>Pulse Converter</i>
Averaging	Life Safety Point	Schedule
Binary Input	Life Safety Zone	<i>Structured View</i>
Binary Output	<i>Load Control</i>	Trend Log
Binary Value	Loop	
Calendar	Multi-state Input	

[Add new 4.5.10.X, p.25]

4.5.10.X Access Door

```
{
  object-identifier: (access-door, )
  object-name: ""
  object-type: access-door
  present-value: 
  description: ""
  status-flags: 
  event-state: 
  reliability: 
  out-of-service: 
  priority-array: 
  relinquish-default: 
  door-status: 
  lock-status: 
  secured-status: 
  door-members: {, ...}
  door-pulse-time: 
  door-extended-pulse-time: 
  door-unlock-delay-time: 
  door-open-too-long-time: 
  door-alarm-state: 
  masked-alarm-values: {,  ...}
  maintenance-required: 
  time-delay: 
  notification-class: 
  alarm-values: {, ...}
  fault-values: {, ...}
```

```
event-enable: {□,□,□}  
acked-transitions: {□,□,□}  
notify-type: □  
event-time-stamps: {□,□,□}  
profile-name: "□"  
}
```

[Add new 4.5.10.X, p.25]

4.5.10.X Accumulator

```
{  
  object-identifier: (accumulator, □)  
  object-name: "□"  
  object-type: accumulator  
  present-value: □  
  description: "□"  
  device-type: "□"  
  status-flags: □  
  event-state: □  
  reliability: □  
  out-of-service: □  
  scale: □  
  units: □  
  prescale: □  
  max-pres-value: □  
  value-change-time: □  
  value-before-change: □  
  value-set: □  
  logging-record: □  
  logging-object: □  
  pulse-rate: □  
  high-limit: □  
  low-limit: □  
  limit-monitoring-interval: □  
  notification-class: □  
  time-delay: □  
  limit-enable: □  
  event-enable: {□,□,□}  
  acked-transitions: {□,□,□}  
  notify-type: □  
  event-time-stamps: {□,□,□}  
  profile-name: "□"  
}
```

[Add new 4.5.10.X, p. 25]

4.5.10.X Load Control

```
{  
  object-identifier: (load-control, □)  
  object-name: "□"  
  object-type: load-control  
  description: "□"  
  present-value: □  
  state-description: "□"  
  status-flags: □  
  event-state: □  
}
```

```
reliability: □
requested-shed-level: □
start-time: □
shed-duration: □
duty-window: □
enabled: □
full-duty-baseline: □
expected-shed-level: □
actual-shed-level: □
shed-levels: {□, □...}
shed-level-descriptions: {"□", "□"...}
notification-class: □
time-delay: □
event-enable: {□,□,□}
acked-transitions: {□,□,□}
notify-type: □
event-time-stamps: {□,□,□}
profile-name: "□"
}
```

[Add new 4.5.10.X, p.25]

4.5.10.X Pulse Converter

```
{
  object-identifier: (pulse-converter, □)
  object-name: "□"
  object-type: pulse-converter
  description: "□"
  present-value: □
  input-reference: □
  status-flags: □
  event-state: □
  reliability: □
  out-of-service: □
  units: □
  scale-factor: □
  adjust-value: □
  count: □
  update-time: □
  count-change-time: □
  count-before-change: □
  cov-increment: □
  cov-period: □
  notification-class: □
  time-delay: □
  high-limit: □
  low-limit: □
  deadband: □
  limit-enable: □
  event-enable: {□,□,□}
  acked-transitions: {□,□,□}
  notify-type: □
  event-time-stamps: {□,□,□}
  profile-name: "□"
}
```


[Add new **4.5.10.X**, p.25]

4.5.10.X Structured View

```
{  
  object-identifier: (structured-view, □)  
  object-name: "□"  
  object-type: structured-view  
  description: "□"  
  node-type: □  
  node-subtype: "□"  
  subordinate-list: {□, □...}  
  subordinate-annotations: {"□", "□"...}  
  profile-name: "□"  
}
```

[Add a new entry to **History of Revisions**, p. 492]

(This History of Revisions is not part of this standard. It is merely informative and does not contain requirements necessary for conformance to the standard.)

HISTORY OF REVISIONS

<i>Protocol</i>		<i>Summary of Changes to the Standard</i>
<i>Version</i>	<i>Revision</i>	
...
1	N/A	<p>Addendum b to ANSI/ASHRAE 135.1-2007 Approved by the ASHRAE Standards Committee June 20, 2009; by the ASHRAE Board of Directors June 24, 2009; and by the American National Standards Institute June 25, 2009.</p> <ol style="list-style-type: none"> 1. Omit certain tests when Averaging and Command properties are fixed or not present. 2. Accommodate Group objects whose members list is not changeable. 3. Revise Alarm Acknowledgement tests. 4. Add new Alarm Acknowledgement "offnormal" tests. 5. Label conditionally-writable properties in the EPICS. 6. Add new object types.

**POLICY STATEMENT DEFINING ASHRAE'S CONCERN
FOR THE ENVIRONMENTAL IMPACT OF ITS ACTIVITIES**

ASHRAE is concerned with the impact of its members' activities on both the indoor and outdoor environment. ASHRAE's members will strive to minimize any possible deleterious effect on the indoor and outdoor environment of the systems and components in their responsibility while maximizing the beneficial effects these systems provide, consistent with accepted standards and the practical state of the art.

ASHRAE's short-range goal is to ensure that the systems and components within its scope do not impact the indoor and outdoor environment to a greater extent than specified by the standards and guidelines as established by itself and other responsible bodies.

As an ongoing goal, ASHRAE will, through its Standards Committee and extensive technical committee structure, continue to generate up-to-date standards and guidelines where appropriate and adopt, recommend, and promote those new and revised standards developed by other responsible organizations.

Through its *Handbook*, appropriate chapters will contain up-to-date standards and design considerations as the material is systematically revised.

ASHRAE will take the lead with respect to dissemination of environmental information of its primary interest and will seek out and disseminate information from other responsible organizations that is pertinent, as guides to updating standards and guidelines.

The effects of the design and selection of equipment and systems will be considered within the scope of the system's intended use and expected misuse. The disposal of hazardous materials, if any, will also be considered.

ASHRAE's primary concern for environmental impact will be at the site where equipment within ASHRAE's scope operates. However, energy source selection and the possible environmental impact due to the energy source and energy transportation will be considered where possible. Recommendations concerning energy source selection should be made by its members.